

OnCast-TC150D

스마트 디지털 앰프

Capture your class and share it with students and public Record your meeting Broadcast corporate event live and on-demand

OnCast-TC150D
Smart Digital Amp



“

OnCast-TC150D는 IR 앰프로서 프리앰프와 증폭앰프를 결합한 디지털 앰프입니다.

”

특징

- Digital IR 앰프로서 프리앰프 와 증폭앰프를 결합
- 비상 방송 시 자동으로 전원이 켜짐
- 유도신호등과 연동 가능
- 조작이 간단
- 전자교탁과 연동될 수 있도록 별도의 제어단자 구성
- 천정 매립형 스피커 또는 일반 스피커와 호환될수 있도록 임피던스 조절 가능

활용

- | | | |
|----------|--|-------------------|
| 학교 | | 전관방송, 시청각실, 강당 방송 |
| 기업 | | 사내 방송, 회의실 방송 |
| 카페,음식점 등 | | 매장방송, 자체 방송 |

사양

Amplifier		OnCast – TC150D	OnCast – TC300D
Rated Output (RMS)		75W + 75W	150W + 150W
Input Sensitivity Impedance	Mic	-50dBm (2.45mV) 2Kohm Balanced	
	IR Mic	-50dBm (2.45mV) 50Kohm Balanced	
	PC Aux	-10dBm (245mV) 5Kohm Balanced	
	Rec/Line(pre) Output	0dBm (1000mV) 600ohm Unbalanced	
Frequency Response		Mic : Less than -3dB (200Hz~20KHz)	
		Line : Less than -3dB (35Hz~20KHz)	
Signal to Noise Ratio		Mic : More then 70dB ("A" weight)	
		Line : More then 80dB ("A" weight)	
T,H,D (at 1KHz Output)		Less than 0.5%	
Tone Controls		Bass : +/- 10dB at 100Hz & Treble : +/- 10dB at 10kHz	
Output Impedance	Low IMP	40hm / 17.4V	40hm / 24.5V
	TNC-150A	40hm – 80hm	40hm – 80hm
	TNC-300a	40hm – 80hm	40hm – 80hm
EMERGENCY SECTION			
Emergency Input		Signal Auto Priority muting Input line 100V (Hi Impedance)	
Emergency Output		Emergency Output LED Display	
GENERAL			
Power Consumption		180W	350W
Power Source		110-240VAC 50/60Hz	
Weight (kg/lbs)		8.2/18.7	15.5/34
Dimensions (WxHxD)mm/inch		420 x 44 x 290 / 17" x 1.72" x 11.4"	

* 제품 사양은 성능 개선을 위해 사전 예고없이 변동될 수 있습니다.

DY | 주 디와이엔텍

서울시 강북구 월계로 53-3 룩일빌딩 2층
 TEL : 02.987.3535 FAX : 02.945.3201
 E-Mail : dy@dyntec.co.kr
 Homepage : www.dyntec.co.kr

Integrated e-Learning Solution